

Smart Home Alarm System



MODEL: L-SA01



Expandable



Easy Setup



Notification Alarm



GSM



Access from anywhere

Adopt Wi-Fi & GSM network, it can be controlled by iOS and Android APP Logan Alarm.
 Support 1 Householder, 99 users.
 Add sensors by scanning QR code.
 Support IP cameras, live video communication.
 24 hours monitoring temperature and humidity.
 Auto detect Wi-Fi & GSM signal status.
 24 hours detecting doors/windows closed or not.
 Low battery alert for sensors, auto detect whether sensors are connected to the alarm panel or not.
 Monitoring AC power, failure or recovery status.
 All the operation logs can be checked on Logan Alarm App.
 Siren prompt and SMS prompt when arm/disarm by remote controller.
 Setup siren alert time(0~254 seconds for optional).
 Delay alarm/arm/disarm functions(0~60 seconds for optional).
 Five languages and voice prompt(English, Russian, German, French and Chinese).
 Support 99 normal sensors, 20 remote controls, 8 fire alarm sensors, 8 medical buttons, 8 emergency buttons, 4 water leakage detectors.
 Support wireless strobe siren.
 GSM Mode:
 When Wi-Fi network failure, auto switch to GSM network.
 3 SMS alarm numbers and 3 alarm call numbers.
 Recorded voice for 10 seconds.



Logan Alert

Download the free

Compatible

